

### 1.3 Country Region Code for 5G band (24h)

Default value = FFh, which means read from INF and registry, more flexible than reading from EEPROM, this is our current InstallShield CCS implementation. We do not recommend customers to read SKU from EEPROM. Value FFh is our default value.

CountryCode— Specify the domain code, can be FFh or one of the followings,

Value	Support Channels
0	36, 40, 44, 48, 52, 56, 60, 64, 149, 153, 157, 161, 165
1	36, 40, 44, 48, 52, 56, 60, 64, 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140
2	36, 40, 44, 48, 52, 56, 60, 64
3	52, 56, 60, 64, 149, 153, 157, 161
4	149, 153, 157, 161, 165
5	149, 153, 157, 161
6	36, 40, 44, 48
7	36, 40, 44, 48, 52, 56, 60, 64, 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140, 149, 153, 157, 161, 165
8	52, 56, 60 64
9	34, 38, 42, 46
10	34, 36, 38, 40, 42, 44, 46, 48, 52, 56, 60, 64

### 1.4 Country Region Code for 2.4G band (25h)

Default value = FFh, which means read from INF and registry, more flexible than reading from EEPROM, this is our current InstallShield CCS implementation. We do not recommend customers to read SKU from EEPROM. Value FFh is our default value.

CountryCode— Specify the domain code, can be FFh or one of the followings,

Value	Support Channels
0	1 – 11
1	1 – 13
2	10 – 11
3	10 – 13
4	14
5	1 – 14
6	3 – 9
7	5 – 13